


### Mini terminal blocks

- mounted onto PR/2 rails, TH/15 type
- **TR.2 and TR.4 terminal block:**  
certificate **CESI 03 ATEX 022 U Ex e**   
I M2 / II 2 G D temperature range of use:  
-40 – +80 °C
- available in grey
- **Coc IEC Ex CES 11.0004U Ex e II**
- maximum operating temperature 100°C

The **/GR** tag indicates the grey version.



Two 6.3 x 0.8 mm or four 2.8 x 0.8 mm flat push-on tab connections compliant with IEC 60760



#### standard version


#### TECHNICAL CHARACTERISTICS

function/type	
rated cross-section	(mm²)
connecting capacity	
flexible	(mm²)
rigid	(mm²)
max. flexible with ferrule (mm²) - ferrule type	
rated voltage / rated current / gauge	conf. to IEC 60947-7-1
rated voltage / rated current / AWG / tightening torque value	UL
(Ex e) rated voltage	(V)
rated impulse withstand voltage / pollution degree	
insulation stripping length	(mm)
tightening torque value (test / max)	(Nm)
Height / width / thickness	TH/15

#### APPROVALS

#### RFI.2/GR

Cat. No. **RF110GR**




feed-through for push-on tab connections	2.5
up to 2.5	
-	
-	
400 V / 20 A / -	
600 V / 20 A / 12 AWG max	
- / -	
6 KV / 3	
-	
- / -	
32 / 28 / 6	



#### TR.2

Cat. No. **TR110**




earth	2.5
0.2-4	
0.2-4	
2.5-WP25/14	
- / - / A3	
- / - / 20-12 AWG / 3.5 lb.in	
- / -	
6 KV / 3	
8	
0.4 / 0.8	
32 / 27 / 5	



#### TR.4

Cat. No. **TR200**



earth	4
0.2-6	
0.2-6	
4-WP40/16	
- / - / A4	
- / - / 20-10 AWG / 5.5 lb.in	
- / -	
6 KV / 3	
9	
0.5 / 1.2	
35 / 35 / 7.3	



#### ACCESSORIES

End sections	grey blue
Permanent cross connection	
Switchable cross connection	
Multiple common bar	250 mm
Shunting screw and sleeve	
Coloured partition	red, green, white
Test plug socket	
Test plug	
Numbering strip	
Warning plate	on adjacent terminal blocks
Marking tag	printed or blank
End bracket	

#### Type Cat. No.

<b>RFN/PT/GR</b>	RF101GR
<b>POF/17</b>	POF17
-	
<b>PMP/17</b>	PMP17
<b>CPM/17</b>	CPM17
<b>DFP/2</b>	DFP2..
<b>PSD/K</b>	PD011
<b>SDD/1</b>	DD001
<b>CNU/8/51</b>	NU0851
-	
<b>CNU/8/61</b>	NU0861
-	
<b>BT/2</b>	BT006

#### Type Cat. No.

<b>TR.2/PT</b>	TR111
-	
-	
-	
<b>DFP/2</b>	DFP2..
-	
<b>CNU/8/51</b>	NU0851
-	
<b>CNU/8/51</b>	NU0851
-	
<b>BT/2</b>	BT006

#### Type Cat. No.

-	
-	
-	
-	
<b>DFP/2</b>	DFP2..
-	
-	
<b>CNU/8/51</b>	NU0851
-	
<b>BT/2</b>	BT006